

MODEL: T2006

CALENDAR DIAL TIME SWITCH

FOR UP TO 42 TIMING OPERATIONS ON 7 DAY SCHEDULE

SINGLE POLE DOUBLE POLE

SWITCH RATING: 20 AMP. 125-480 VOLTS A.C.

1/2 HP-125V 1 HP-250V.

CLOCK MOTOR: 208-277V. - 60 HZ.



MINIMUM ON OR OFF TIME IS 2 HOURS.
EXTENDABLE IN 2 HOUR INCREMENTS;





FIG. 1



WIRING DIAGRAM

WIRING INSTRUCTIONS

This Time Switch can be wired to control two circuits as Single Pole Double throw, or to control one circuit as Single Pole Single Throw. Either normally open (NO) or normally closed (NC).

PROGRAMMING INSTRUCTIONS

- 1. TO PROGRAM TIME SWITCH,** Depress tripper(s) into dial at desired time(s) operation(s) is/are required.
 - **ON TIME:** First tripper turns on the load for 135-145 minutes. Each additional tripper will lengthen the on time by 2 hours.
 - **OFF TIME:** First tripper in raised position turns off the load for 95-105 minutes. Each additional space will lengthen the of time by 2 hours.
- 2. SET TIME-OF-DAY:** Turn dial in clockwise direction only and align the exact day -of-week and time-of-day on dial (the time when switch is being put in operation) to the "TIME" indicator.

OPERATING INSTRUCTIONS

TO CONTROL LOADS MANUALLY, Move manual lever (See Figure 1) up. This lever will close normally open circuit and open the normally closed circuit. To return, to automatic control, move lever back to its original position .

TO REMOVE MECHANISM FROM CASE, disconnect electricity and all wiring. Depress retainer spring at upper left, or unscrew mounting screws, then grasp dial and pull mechanism out.

IN CASE OF POWER FAILURE, or retard/advance time reset dial. See step (2) of programming instructions.

INTERMATIC INCORPORATED

SPRING GROVE, ILLINOIS 60081-9698